



**Effects of Fiberglass Poles on Radiation Patterns
of Log-Periodic Antennas**

by **Christos E. Maragoudakis**

ARL-TN-0357

July 2009

NOTICES

Disclaimers

The findings in this report are not to be construed as an official Department of the Army position unless so designated by other authorized documents.

Citation of manufacturer's or trade names does not constitute an official endorsement or approval of the use thereof.

Destroy this report when it is no longer needed. Do not return it to the originator.

Army Research Laboratory

White Sands Missile Range, NM 88002-5513

ARL-TN-0357

July 2009

Effects of Fiberglass Poles on Radiation Patterns of Log-Periodic Antennas

Christos E. Maragoudakis
Survivability/Lethality Analysis Directorate, ARL

REPORT DOCUMENTATION PAGE			<i>Form Approved</i> OMB No. 0704-0188		
Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing the burden, to Department of Defense, Washington Headquarters Services, Directorate for Information Operations and Reports (0704-0188), 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to any penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number. PLEASE DO NOT RETURN YOUR FORM TO THE ABOVE ADDRESS.					
1. REPORT DATE (DD-MM-YYYY) July 2009		2. REPORT TYPE Final		3. DATES COVERED (From - To) May 15–30, 2009	
4. TITLE AND SUBTITLE Effects of Fiberglass Poles on Radiation Patterns of Log-Periodic Antennas				5a. CONTRACT NUMBER	
				5b. GRANT NUMBER	
				5c. PROGRAM ELEMENT NUMBER	
6. AUTHOR(S) Christos E. Maragoudakis				5d. PROJECT NUMBER	
				5e. TASK NUMBER	
				5f. WORK UNIT NUMBER	
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) U.S. Army Research Laboratory Information and Electronic Protection Division Survivability/Lethality Analysis Directorate (ATTN: RDRL-SLE-S) White Sands Missile Range, NM 88002-5513				8. PERFORMING ORGANIZATION REPORT NUMBER ARL-TN-0357	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES)				10. SPONSOR/MONITOR'S ACRONYM(S)	
				11. SPONSOR/MONITOR'S REPORT NUMBER(S)	
12. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution is unlimited.					
13. SUPPLEMENTARY NOTES					
14. ABSTRACT The effects of fiberglass poles of various cross-section and chemical composition on the radiation pattern of log-periodic antennas are presented in this document. The antennas were mounted with the poles parallel to the antenna boom and vertical to the radiating elements. Normalized antenna patterns depicting the effects of the poles on the radiation pattern in the 100 megahertz (MHz) to 1 gigahertz (GHz) frequency range are included in the appendix of this document.					
15. SUBJECT TERMS fiberglass, antenna pattern, log-periodic					
16. SECURITY CLASSIFICATION OF:			17. LIMITATION OF ABSTRACT UU	18. NUMBER OF PAGES 16	19a. NAME OF RESPONSIBLE PERSON Christos E. Maragoudakis
a. REPORT Unclassified	b. ABSTRACT Unclassified	c. THIS PAGE Unclassified			19b. TELEPHONE NUMBER (Include area code) (575) 678-3145

Contents

List of Figures	iv
1. Introduction	1
2. Experimental Set-up	1
3. Results	2
4. Conclusions	3
5. Recommendations	3
Appendix. Antenna Patterns	5
List of Symbols, Abbreviations, and Acronyms	9
Distribution	10

List of Figures

Figure 1. Experiment set-up.....	1
Figure 2. Log periodic antenna mounted with a tubular fiberglass pole.	2
Figure 3. Antenna pattern for 200 MHz using tubular fiberglass pole 1.	3
Figure A-1. Antenna pattern for 200 MHz using tubular fiberglass pole 1.....	5
Figure A-2. Antenna pattern for 900 MHz using tubular fiberglass pole 1.....	5
Figure A-3. Antenna pattern for 200 MHz using tubular fiberglass pole 2.....	6
Figure A-4. Antenna pattern for 900 MHz using tubular fiberglass pole 2.....	6
Figure A-5. Antenna pattern for 200 MHz using square fiberglass pole.....	7
Figure A-6. Antenna pattern for 900 MHz using square fiberglass pole.....	7
Figure A-7. Antenna pattern for 200 MHz using the PVC pole.	8
Figure A-8. Antenna pattern for 900 MHz using the PVC pole.	8

1. Introduction

Antennas are mounted in various ways depending on the antenna type and the intended application. The common method of mounting log periodic and Yagi antennas is by supporting them from the balance point on the boom using metal, wooden, or fiberglass poles. This technical note presents the results of an investigation that was performed to determine the effects of fiberglass poles on the radiation pattern of a log periodic antenna when the pole is parallel to the boom. The investigation was performed at the Electromagnetic Vulnerability Assessment Facility (EMVAF) of the U.S. Army Research Laboratory (ARL) Survivability/Lethality Analysis Directorate (SLAD) at White Sands Missile Range, NM.

2. Experimental Set-up

The test equipment used in the investigation included three fiberglass poles of different composition and cross-section, a Poly Vinyl Chloride (PVC) pole and two log periodic antennas. The transmit antenna was an Amplifier Research Log periodic, model AT-1080 while the receive antenna was a Creative Design Corp. model CLP 5130-2. The transmit antenna was mounted on the mast at the mezzanine, while the receive antenna was mounted on the Howland antenna measurement tower at the end of the other end of the chamber. A diagram of the measurement set-up used is shown in figure 1.




Figure 1. Experiment set-up.

The receive antenna was mounted on the tower using either one of the fiberglass poles or the PVC pole. The poles were placed parallel to the boom (a beam that the radiating elements are

attached to) of the antenna and vertical relative to the antenna radiating elements. The two tubular fiberglass poles had a 2-inch outside diameter and a wall thickness was 0.25 inches, while the third fiberglass pole had a 3×3-inch cross-section and a 0.25-inch wall thickness. The last pole used was a schedule 40 PVC pole with an outside diameter of 1.875 inches. Figure 2 depicts the receive antenna mounted on the tower using one of the tubular poles.



Figure 2. Log periodic antenna mounted with a tubular fiberglass pole.

3. Results

All measurements were made with both antennas vertically polarized. During the measurements the frequency was varied from 100 megahertz (MHz) to 1 gigahertz (GHz) in 100 MHz steps while the receive antenna was rotated from 0° to 360° in 2° steps in the azimuth plane. Figure 3 depicts the normalized antenna pattern measured at 200 MHz. Additional antenna patterns are shown in the appendix.




Figure 3. Antenna pattern for 200 MHz using tubular fiberglass pole 1.

4. Conclusions

As seen from the antenna patterns measured, the patterns are being affected by the presence of the fiberglass pole. The amount of antenna pattern degradation is a function of carbon content in the fiberglass pole, frequency of operation and position of the antenna relative to the pole. Even though the effect is minimal, less than 2 decibels (dB), for the configuration tested, it may be critical for other applications.

5. Recommendations

Because preliminary results show that fiberglass poles could affect the antenna patterns, it is recommended that additional studies be made so that the effects of fiberglass on the antenna performance are better understood. The studies should include the placement of other commonly used antennas, such as vertical antennas, at various distances from the fiberglass poles.

INTENTIONALLY LEFT BLANK.

Appendix. Antenna Patterns




Figure A-1. Antenna pattern for 200 MHz using tubular fiberglass pole 1.




Figure A-2. Antenna pattern for 900 MHz using tubular fiberglass pole 1.




Figure A-3. Antenna pattern for 200 MHz using tubular fiberglass pole 2.




Figure A-4. Antenna pattern for 900 MHz using tubular fiberglass pole 2.




Figure A-5. Antenna pattern for 200 MHz using square fiberglass pole.




Figure A-6. Antenna pattern for 900 MHz using square fiberglass pole.




Figure A-7. Antenna pattern for 200 MHz using the PVC pole.




Figure A-8. Antenna pattern for 900 MHz using the PVC pole.

List of Symbols, Abbreviations, and Acronyms

ARL	U.S. Army Research Laboratory
dB	decibels
EMVAF	Electromagnetic Vulnerability Assessment Facility
GHz	Gigahertz
MHz	megahertz
PVC	Poly Vinyl Chloride
SLAD	Survivability/Lethality Analysis Directorate

<u>No. of Copies</u>	<u>Organization</u>
1 PDF	ADMNSTR DEFNS TECHL INFO CTR DTIC OCP 8725 JOHN J KINGMAN RD STE 0944 FT BELVOIR VA 22060-6218
3 HCs	US ARMY RSRCH LAB ATTN RDRL CIM P TECHL PUB ATTN RDRL CIM L TECHL LIB ATTN IMNE ALC HRR MAIL & RECORDS MGMT 2800 POWDER MILL ROAD ADELPHI MD 20783-1197
1 CD	US ARMY RSRCH LAB ATTN RDRL CIM G TECHL LIB T LANDFRIED APG MD 21005-5066
1 CD 1 WORD VERSION	US ARMY RSRCH LAB MELE ASSOCIATES INC ATTN RDRL SLE E M MORALES BLDG 1622 ROOM 216 WSMR NM 88002-5501
1 HC	US ARMY RSRCH LAB ATTN RDRL SLE S J GONZALEZ BLDG 1624 RM 204 WSMR NM 88002-5513
2 HCs	US ARMY RSRCH LAB ATTN RDRL SLE S C MARAGOUDAKIS BLDG 1628 RM 203 WSMR NM 88002-5513
Total:	10 (1 PDF, 2 CDs, 6 HCs, 1 Word Version)